

# HP LaserJet Pro MFP M426 Series



**A fast, efficient MFP with robust security and innovative toner for more pages.<sup>2</sup>**

Fast print, scan, copy, and fax performance plus robust, comprehensive security built for how you work. This MFP finishes key tasks faster and guards against threats.<sup>1</sup> Original HP Toner cartridges with JetIntelligence give you more pages.<sup>2</sup>



HP LaserJet Pro MFP M426fdn



HP LaserJet Pro MFP M426fdw

### Speed through more tasks. Keep data protected.

- Scan fast with single-pass, two-sided scanning, and send your work quickly to more places—without using your PC. Scan documents directly to email, network folders, and the cloud.<sup>3</sup>
- Breeze through multipage documents with two-sided printing that's faster than the competition.<sup>1</sup>
- Grab pages and go—without waiting around. This MFP wakes up and prints faster than the competition.<sup>1</sup>
- Keep printing safe—from boot up to shutdown—with embedded features like LDAP authentication.

### Easy management. Efficient printing.

- Easily manage print jobs directly at the MFP—just tap and swipe the 7.6 cm (3-inch) touchscreen.<sup>5</sup>
- Easily print Microsoft® Word and PowerPoint® documents—now directly from your USB drive.<sup>4</sup>
- Easily manage devices and settings using HP Web Jetadmin with a suite of essential management features.<sup>6</sup>
- Print using less energy than competitors—enhanced by Original HP Toner cartridges with JetIntelligence.<sup>7</sup>

### More pages, performance, and protection

- Get the most prints for your money—with Original HP High Yield Black Toner cartridges with JetIntelligence.<sup>2</sup>
- Count on professional quality at high speeds with precision black toner.
- Help ensure you're getting the authentic HP quality you paid for with innovative anti-fraud technology.
- Print right away with preinstalled toner cartridges. Replace them with optional high-yield cartridges.

### Stay connected with easy mobile printing options

- Easily print from a variety of smartphones and tablets—generally no setup or apps required.<sup>8</sup>
- Count on wireless direct printing in the office—from mobile devices—without accessing the company network.<sup>10</sup>
- Help workers print with just a touch of their NFC-enabled mobile device to the printer—no network needed.<sup>11</sup>
- Easily access, print, and share resources with Ethernet and wireless networking.<sup>9</sup>

<sup>1</sup> Based on HP internal testing of top three leading competitors' first page out from sleep mode and duplex print and copy speed completed 8/2015. Subject to device settings. Actual results may vary. For details see [hp.com/go/ljclaims](http://hp.com/go/ljclaims) <sup>2</sup> Based on cartridge yields for HP 80X compared with HP 26X Original HP LaserJet Toner Cartridges. For more information, see [hp.com/go/learnaboutsupplies](http://hp.com/go/learnaboutsupplies) <sup>3</sup> Requires an Internet connection to the printer. Services may require registration. App availability varies by country, language, and agreements. For details, see [hpconnected.com](http://hpconnected.com) <sup>4</sup> Microsoft and PowerPoint are U.S. registered trademarks of the Microsoft group of companies. Feature works with Microsoft Word and PowerPoint 2003 and later. Only Latin language fonts are supported. <sup>5</sup> Requires a wireless access point and an Internet connection to the printer. Services require registration. App availability varies by country, language, and agreements and requires a firmware upgrade. For details, visit [hpconnected.com](http://hpconnected.com) <sup>6</sup> HP Web Jetadmin is free and available for download at [hp.com/go/webjetadmin](http://hp.com/go/webjetadmin) <sup>7</sup> Based on HP testing using the ENERGY STAR® program's Typical Electricity Consumption (TEC) method or as reported in [energystar.gov](http://energystar.gov) of top three leading competitors as of 8/2015. Actual results may vary. For details see [hp.com/go/ljclaims](http://hp.com/go/ljclaims) <sup>8</sup> Wireless operations are compatible with 2.4 GHz operations only. App or software and HP ePrint account registration may also be required. Some features require purchase of an optional accessory. Learn more at [hp.com/go/mobileprinting](http://hp.com/go/mobileprinting) <sup>9</sup> Feature available only for the HP LaserJet Pro MFP M426fdw. Wireless performance is dependent on physical environment and distance from access point, and may be limited during active VPN connections. <sup>10</sup> Feature available only for the HP LaserJet Pro MFP M426fdw. Mobile device needs to be connected directly to the Wi-Fi network of a wireless direct-capable MFP or printer prior to printing. Depending on mobile device, an app or driver may also be required. Learn more at [hp.com/go/businessmobileprinting](http://hp.com/go/businessmobileprinting) <sup>11</sup> Feature available only for the HP LaserJet Pro MFP M426fdw. Requires a compatible NFC-printing-enabled mobile device. For a list of compatible NFC-printing-enabled mobile devices, see [hp.com/go/nfcprinting](http://hp.com/go/nfcprinting)

## Product walkaround

- 1 Intuitive 7.6 cm (3-inch) colour touchscreen tilts for easier viewing while sitting or standing
- 2 50-sheet automatic document feeder (ADF)
- 3 Flatbed scanner handles up to 216 x 297 mm paper
- 4 150-sheet output bin
- 5 Built-in wireless direct printing<sup>3</sup> and NFC touch-to-print<sup>4</sup>
- 6 Front door release button (access to HP JetIntelligence Toner cartridges)
- 7 Automatic two-sided printing
- 8 Built-in wireless networking<sup>2</sup>
- 9 Easy-access USB port
- 10 Power on/off button
- 11 100-sheet multipurpose tray 1
- 12 250-sheet input tray 2
- 13 USB port for job storage with PIN printing<sup>7</sup>
- 14 Hi-Speed USB 2.0 printing port
- 15 Ethernet network port
- 16 Telephone “line out” port
- 17 Fax “line in” port
- 18 1200 MHz processor, 256 MB memory
- 19 Rear door (access to print path)
- 20 Dust cover for tray 2—flips up when A4 paper is loaded

HP LaserJet Pro MFP M426fdw shown



Front view



Rear view

## Series at a glance



Model	HP LaserJet Pro MFP M426fdn	HP LaserJet Pro MFP M426fdw
<b>Product number</b>	F6W14A	F6W15A
<b>100-sheet multipurpose tray 1, 250-sheet tray 2</b>	✓	✓
<b>550-sheet tray 3</b>	Optional	Optional
<b>Print speed<sup>5</sup></b>	Up to 38 pages per minute (ppm), A4	Up to 38 ppm, A4
<b>Scan speed (A4)<sup>6</sup></b>	Simplex: up to 26/21 ppm, black/colour Single-pass duplex: up to 47/30 images per minute (ipm), black/colour	Simplex: up to 26/21 ppm, black/colour Single-pass duplex: up to 47/30 ipm, black/colour
<b>Networking</b>	Built-in 10/100/1000 Base-TX Gigabit Ethernet	Built-in 10/100/1000 Base-TX Gigabit Ethernet, wireless 802.11b/g/n <sup>4</sup>
<b>Mobile printing<sup>1</sup></b>	HP ePrint, Apple AirPrint, Mopria-certified, Google Cloud Print™ 2.0	Wireless direct printing, NFC touch-to-print, HP ePrint, Apple AirPrint, Mopria-certified, Google Cloud Print 2.0

<sup>1</sup> Wireless operations are compatible with 2.4 GHz operations only. App or software and HP ePrint account registration may also be required. Some features require purchase of an optional accessory. Learn more at [hp.com/go/mobileprinting](http://hp.com/go/mobileprinting) <sup>2</sup> Wireless networking is supported on the M426fdw model only. Wireless performance is dependent on physical environment and distance from access point, and may be limited during active VPN connections. <sup>3</sup> Wireless direct printing is supported on the M426fdw model only. Mobile device needs to be connected directly to the Wi-Fi network of a wireless direct-capable MFP or printer prior to printing. Depending on mobile device, an app or driver may also be required. Learn more at [hp.com/go/businessmobileprinting](http://hp.com/go/businessmobileprinting) <sup>4</sup> NFC touch-to-print is supported on the M426fdw model only. Requires a compatible NFC-printing-enabled mobile device. For a list of compatible NFC-printing-enabled mobile devices, see [hp.com/go/nfcprinting](http://hp.com/go/nfcprinting) <sup>5</sup> Printing speed measured using ISO/IEC 24734 and excludes first set of test documents. For more information, see [hp.com/go/printerclaims](http://hp.com/go/printerclaims). Exact speed varies depending on the system configuration, software application, driver, and document complexity. <sup>6</sup> Scan speeds measured from ADF. Actual processing speeds may vary depending on scan resolution, network conditions, computer performance, and application software.

## HP Services

Downtime can have serious consequences, so HP provides support beyond the standard warranty. You benefit from reduced risk, maximized uptime, predictable service delivery and no unbudgeted repair costs. Choose from:

**Optimized Care (optimum performance and stability):** 4 hour Onsite Support, Maintenance Kit Replacement Service, Installation with Network Configuration Service

**Standard Care (high level of uptime):** Next Business Day Onsite Support, Maintenance Kit Replacement Service, Installation with Network Configuration Service

**Basic Care (minimum recommended support):** Next Business Day Onsite Support

**4 hr Onsite Support:** Onsite support within four hours after a service call received within the coverage window

**Next Business Day Onsite Support:** Onsite service the next business day after the service call is received

**Maintenance Kit Replacement Service:** Onsite replacement of your printer's maintenance kit including parts, materials, and labor

**Installation with Network Configuration Service:** Assembly, network configuration, and basic administrator familiarization

For more information about HP Care Pack, HP Contractual, or HP Managed Print Services, visit [hp.com/go/printservices](http://hp.com/go/printservices)



Windows 8



## Top Features

Shift your office into high gear with an MFP that doesn't keep you waiting. Print your first page and two-sided prints faster than the competition, and scan quickly.<sup>1</sup> Help keep your device, data, and documents safe—from boot up to shutdown.

Easily produce the documents you need to keep work flowing while conserving power. This energy-efficient MFP is easy to manage and use. Print Microsoft® Word and PowerPoint® documents directly from the USB port,<sup>3</sup> using the intuitive touchscreen.<sup>4</sup>

Print more consistent, high-quality pages than ever before.<sup>2</sup> Specially designed Original HP Toner cartridges with JetIntelligence deliver better performance, higher energy efficiency, and authentic HP quality—which the competition can't match.<sup>2</sup>

Keep business nimble when needs shift or opportunity strikes—in the office or on the go.<sup>5</sup> Print wirelessly with or without accessing the network,<sup>6,7</sup> and stay connected with Ethernet capabilities. Print with a touch from mobile devices.<sup>5,8</sup>

### Product

F6W14A	HP LaserJet Pro MFP M426fdn
F6W15A	HP LaserJet Pro MFP M426fdw

### Accessories

D9P29A	HP LaserJet 550-sheet Feeder Tray
P0R81AA	HP v222w 16GB Mini USB Drive

### Supplies<sup>9</sup>

CF226A	HP 26A Black LaserJet Toner Cartridge (~3,100 pages)
CF226X	HP 26X Black LaserJet Toner Cartridge (~9,000 pages)

### HP Care Packs

U8TQ9E	HP 3-year Next Business Day LaserJet M426 MFP Hardware Support
U8TR0E	HP 4-year Next Business Day LaserJet M426 MFP Hardware Support
U8TR1E	HP 5-year Next Business Day LaserJet M426 MFP Hardware Support
U8TR4PE	HP 1-year Post Warranty Next Business Day LaserJet M426 MFP Hardware Support

Protect your investment with HP Care Pack. Let HP certified engineers resolve your technical issues. For more details on HP Care Pack, go to [hp.com/go/cpc](http://hp.com/go/cpc)

### Paper

Contact HP via phone: Asia: 65 6253 8500

### Solutions

HP Web Jetadmin: [hp.com/go/wja](http://hp.com/go/wja)

HP Universal Print Driver: [hp.com/go/upd](http://hp.com/go/upd)

HP Imaging and Printing Security Center: [hp.com/go/ipsc](http://hp.com/go/ipsc)

<sup>1</sup> Based on HP internal testing of top three leading competitors' first page out from sleep mode and duplex print and copy speed completed 8/2015. Subject to device settings. Actual results may vary. For details see [hp.com/go/ujclaims](http://hp.com/go/ujclaims) <sup>2</sup> Based on cartridge yields for HP 80X compared with HP 26X Original HP LaserJet Toner Cartridges. For more information, see [hp.com/go/learnaboutsupplies](http://hp.com/go/learnaboutsupplies) <sup>3</sup> Microsoft and PowerPoint are U.S. registered trademarks of the Microsoft group of companies. Feature works with Microsoft Word and PowerPoint 2003 and later. Only Latin language fonts are supported. <sup>4</sup> Requires a wireless access point and an Internet connection to the printer. Services require registration. App availability varies by country, language, and agreements and requires a firmware upgrade. For details, visit [hpconnected.com](http://hpconnected.com) <sup>5</sup> Wireless operations are compatible with 2.4 GHz operations only. App or software and HP ePrint account registration may also be required. Some features require purchase of an optional accessory. Learn more at [hp.com/go/mobileprinting](http://hp.com/go/mobileprinting) <sup>6</sup> Feature available only for the HP LaserJet Pro MFP M426fdw. Wireless performance is dependent on physical environment and distance from access point, and may be limited during active VPN connections. <sup>7</sup> Feature available only for the HP LaserJet Pro MFP M426fdw. Mobile device needs to be connected directly to the Wi-Fi network of a wireless direct-capable MFP or printer prior to printing. Depending on mobile device, an app or driver may also be required. Learn more at [hp.com/go/businessmobileprinting](http://hp.com/go/businessmobileprinting) <sup>8</sup> Feature available only for the HP LaserJet Pro MFP M426fdw. Requires a compatible NFC-printing-enabled mobile device. For a list of compatible NFC-printing-enabled mobile devices, see [hp.com/go/nfcprinting](http://hp.com/go/nfcprinting) <sup>9</sup> Declared yield value in accordance with ISO/IEC 19752. Actual yields vary considerably based on images printed and other factors. For more information, visit [hp.com/go/learnaboutsupplies](http://hp.com/go/learnaboutsupplies)

# HP LaserJet Pro MFP M426 Series

Technical specifications	HP LaserJet Pro MFP M426fdn (F6W14A)	HP LaserJet Pro MFP M426fdw (F6W15A)
<b>Functions</b>	Print, Copy, Fax, Scan	
<b>Print</b>	Automatic (standard)	
Duplex print options	Automatic (standard)	
Print speed <sup>1</sup>	<b>Black (normal, A4):</b> Up to 38 ppm; <b>Black (normal, letter):</b> Up to 40 ppm; <b>Black Duplex (A4):</b> Up to 30 ipm; <b>Black Duplex (letter):</b> Up to 32 ipm	
First page out <sup>2</sup>	<b>Black (A4, ready):</b> As fast as 5.6 sec; As fast as 13.2 sec (100 V); <b>Black (A4, sleep):</b> As fast as 8.0 sec	
Print technology	Laser	
Print resolution	<b>Black (best):</b> HP FastRes 1200; <b>Black (Fine Lines):</b> Up to 1200 x 1200 dpi	
Print resolution technologies	HP FastRes 1200, HP ProRes 1200, 600 dpi	
Print cartridges number	1 (black)	
Standard print languages	HP PCL 5, HP PCL 6, HP postscript level 3 emulation, direct PDF (v 1.7) printing, URF, PCLM, PWG, Native Office	
Printer management	Printer Administrator Resource Kit (Driver Configuration Utility, Driver Deployment Utility, Managed Printing Administrator); HP Web JetAdmin Software; HP Proxy Agent Software; HP Imaging and Printing Security Center; HP Utility (Mac); HP Device Toolbox	
Printer smart software features	Auto-duplex printing, N-up printing, collation, HP ePrint, Apple AirPrint™, Mopria certified, Google Cloud Print, HP Auto-On/Off Technology, Intuitive 3" touchscreen control panel, Print from Cloud using business apps on the control panel, HP JetAdvantage Private Print, Job Storage with PIN printing, <sup>11</sup> Print from USB, JetIntelligence Cartridge Technology	
<b>Scan</b>	Auto-duplex printing, N-up printing, collation, HP ePrint, Apple AirPrint™, Mopria certified, Google Cloud Print, wireless direct printing, HP Auto-On/Off Technology, Intuitive 3" touchscreen control panel, Print from Cloud using business apps on the control panel, HP JetAdvantage Private Print, <sup>11</sup> Job Storage with PIN printing, Print from USB, JetIntelligence Cartridge Technology	
Scan type/technology	<b>Type:</b> Flatbed, ADF; <b>Technology:</b> Contact Image Sensor (CIS)	
Scan speed <sup>3</sup>	<b>Normal, A4:</b> Up to 26 ppm/47 ipm (b&w), up to 21 ppm/30 ipm (colour)	
Scan resolution	<b>Enhanced:</b> Up to 1200 x 1200 dpi; <b>Hardware:</b> Up to 1200 x 1200 dpi; <b>Optical:</b> Up to 1200 x 1200 dpi	
Scan size	<b>ADF:</b> 216 x 355.6 mm (8.5 x 14 in); <b>Flatbed:</b> 297 x 216 mm (11.7 x 8.5 in)	
Scan input modes	For Scan software (included in the box) support: Windows [JPG, RAW(BMP), PDF, TIFF, PNG, RTF] and Mac [JPG, JPG-2000, TIFF, PNG, PDF, Searchable PDF, RTF, TXT]	
<b>Copy</b>	Instant-on copy; Duplex copy; up to 99 multiple copies; Scan once print many; Collation; Reduce/enlarge from 25 to 400% (with page size presets); Fit to page; Customizable copy presets (two or four pages to one page); Contrast (lighter/darker); Resolution (copy quality); Network protocols supported; ID copy; Optimize copy selection (with presets: autoselect, mixed, printed picture, photograph, text), 50-page automatic document feeder with dual-head scanner	
Copy speed <sup>4</sup>	<b>Black (normal, A4):</b> Up to 38 cpm; <b>Black (normal, letter):</b> Up to 40 cpm; <b>Black Duplex (A4):</b> Up to 30 cpm; <b>Black Duplex (letter):</b> Up to 32 cpm	
First copy out	<b>Black (A4):</b> As fast as 7.2 sec; <b>Black (A4, sleep):</b> As fast as 9.7 sec	
Copy resolution	<b>Black (text &amp; graphics):</b> 600 x 600 dpi; <b>Colour (text &amp; graphics):</b> 600 x 600 dpi	
Max no of copies	Up to 99 copies	
Copier resize	25 to 400%	
Copier settings	Light/Darker; Two Sided; ID copy; Optimize	
<b>Fax</b>	Permanent fax memory backup; Auto fax reduction; Auto redialing; Delayed sending; Fax forwarding; TAM interface; Poling; Junk barrier; Distinctive ring detection; Cover page wizard; Block fax; Billing codes; Save and load; Poll receive; Fax activity reports; Dial prefix setting; Print fax log; Digital Fax Setup Wizard; Fax Setup Wizard; HP Send Fax	
Fax speed <sup>5</sup>	33.6 kbps; 3 sec per page (letter)	
Fax resolution	<b>Black (best):</b> Up to 300 x 300 dpi (halftone enabled); <b>Black (standard):</b> 203 x 98 dpi; <b>Black &amp; White (fine):</b> 203 x 196 dpi; <b>Black &amp; White (superfine):</b> 300 x 300 dpi (no halftone); <b>Black Photo Grayscale:</b> 300 x 300 dpi (halftone enabled)	
Fax features	<b>Auto fax reduction supported:</b> Yes; <b>Auto-Redialing:</b> Yes; <b>Fax delayed sending:</b> Yes; <b>Distinctive ring detection supported:</b> Yes; <b>Fax forwarding supported:</b> Yes; <b>Junk barrier supported:</b> Yes; <b>Maximum speed dialing numbers:</b> Up to 120 numbers (119 group dial); <b>PC interface supported:</b> Yes; <b>Fax polling supported:</b> Yes (poll to receive only)	
<b>Connectivity</b>	1 Hi-Speed USB 2.0; 1 Host USB; 1 Gigabit Ethernet 10/100/1000T network; Easy-access USB	
Standard connectivity	HP ePrint, Apple AirPrint™, Mopria-certified, Google Cloud Print 2.0, Mobile Apps	
Mobile print capability <sup>6</sup>	Standard (Built-in Gigabit Ethernet)	
Network ready	Via built-in 10/100/1000Base-TX Ethernet, Gigabit; Auto-crossover Ethernet	
Network capabilities	<b>Standard/Maximum:</b> 256 MB	
<b>Memory</b>	Up to 80,000 pages; <b>Recommended monthly page volume:</b> <sup>8</sup> 750 to 4,000 pages	
<b>Duty cycle</b> <sup>7</sup>	1200 Mhz	
<b>Processor speed</b>	100-sheet tray 1, 250-sheet input tray 2; <b>Optional:</b> third 550-sheet tray	
<b>Paper handling</b>	150-sheet output bin	
Input	Paper (plain, EcoEFFICIENT, light, heavy, bond, coloured, letterhead, preprinted, prepunched, recycled, rough); envelopes; labels; transparencies	
Output	<b>Tray 1:</b> 60 to 175 g/m <sup>2</sup> ; <b>Tray 2, optional 550-sheet tray 3:</b> 60 to 120 g/m <sup>2</sup>	
Media type	<b>Tray 1:</b> 76.2 x 127 to 215.9 x 355.6 mm; <b>Tray 2, 3:</b> 104.9 x 148.59 to 215.9 x 355.6 mm	
Media weight	420 x 390 x 323 mm (16.54 x 15.35 x 12.72 in)	
Media sizes custom	12.86 kg (28.35 lb)	
<b>Dimensions (W x D x H)</b>	HP LaserJet Pro M426fdn; Preinstalled HP 26A Black LaserJet Toner Cartridge (~3,100 pages); Getting Started Guide; Setup Poster; Support Flyer; Warranty Guide; Printer documentation and software on CD-ROM; Power cord; Phone cord; USB cable	
<b>Weight</b>	HP LaserJet Pro M426fdw; Preinstalled HP 26A Black LaserJet Toner Cartridge (~3,100 pages); Getting Started Guide; Setup Poster; Support Flyer; Warranty Guide; Printer documentation and software on CD-ROM; Power cord; Phone cord; USB cable	
<b>What's in the box</b>	One-year warranty, return to HP Authorized Service Provider	
<b>Warranty features</b>		
<b>Systems</b>		
Compatible operating systems	Windows OS compatible with In-Box Driver; Windows XP SP3 all 32-bit editions (XP Home, XP Pro, etc.); Windows Vista all 32-bit editions (Home Basic, Premium, Professional, etc.); Windows 7 all 32- & 64-bit editions; Windows 8/8.1 all 32- & 64-bit editions (excluding RT OS for Tablets); Windows 10 all 32- & 64-bit editions (excluding RT OS for Tablets); Windows OS compatible with Universal Print Driver (HP.com); Windows XP SP3 32- & 64-bit editions (XP Home, XP Pro, etc.); Windows Vista all 32- & 64-bit editions (Home Basic, Premium, Professional, etc.); Windows 7 all 32- & 64-bit editions; Windows 8/8.1 all 32- & 64-bit editions (excluding RT OS for Tablets); Windows 10 all 32- & 64-bit editions (excluding RT OS for Tablets); Mac OS (HP Printer Drivers available from HP.com and Apple Store); OS X 10.8 Mountain Lion; OS X 10.9 Mavericks; OS X 10.10 Yosemite; Mobile OS (In-OS drivers); iOS, Android, Windows 8/8.1/10 RT; Linux OS (In-OS HPLIP; Auto install; BOSS (3.0, 5.0); DEBIAN (6.0, 6.0.1, 6.0.2, 6.0.3, 6.0.4, 6.0.5, 6.0.6, 6.0.7, 6.0.8, 6.0.9, 6.0.10, 7.0, 7.1, 7.2, 7.3, 7.4, 7.5, 7.6); FEDORA (17, 18, 19, 20); LINUX MINT (13, 14, 15, 16, 17); SUSE LINUX (12.2, 12.3, 13.1); UBUNTU (10.04, 11.10, 12.04.12.10, 13.04, 13.10, 14.04, 14.10); Manual install; MANDRIVA LINUX (2010.0, 2011.0); MEPIS (6.0, 6.5, 7.0, 8.0); PCLINUXOS (2006.0, 2006, 2007.0, 2007, 2008.0, 2008, 2009.0, 2009); RED HAT (8.0, 9.0); RED HAT ENTERPRISE LINUX (5.0, 6.0, 7.0); SLACKWARE LINUX (9.0, 9.1, 10.0, 10.1, 10.2, 11, 12, 12.1); GOS (0.4.1); IGOS (1.0); LIMPUS LINUX (9.4, 9.5); LINUX FROM SCRATCH(0); Other OS; UNIX	
Minimum system requirements	<b>PC:</b> Windows 10 (32-bit/64-bit), Windows 8.1 (32-bit/64-bit), Windows 8 (32-bit/64-bit), Windows 7 (32-bit/64-bit); 1 GHz processor; 1 GB RAM (32-bit) or 2 GB RAM (64-bit); 400 MB available hard disk space, CD/DVD-ROM or Internet, USB or Network port; Windows Vista (32-bit): 1 GHz 32-bit (x86) processor; 1 GB RAM (32-bit); 400 MB available hard disk space, CD/DVD-ROM or Internet, USB or Network port; Windows XP (32-bit) (SP2); Pentium 233 Mhz processor; 512 MB RAM 400 MB available hard disk space, CD/DVD-ROM or Internet, USB or Network port; Windows Server 2003 (32-bit) (SP1 or greater); Windows Server 2003 R2 (32-bit), Windows Server 2008 (32-bit) (SP1 or greater); 1 GHz 32-bit (x86) processor; 1 GB RAM (32-bit); 400 MB available hard disk space, CD/DVD-ROM or Internet, USB or Network port; Windows Server 2008 (64-bit) (SP1 or greater), Windows Server 2008 R2 (64-bit), Windows Server 2008 R2 (64-bit) (SP1); 1 GHz 64-bit (x64) processor; 2 GB RAM (64-bit); 400 MB available hard disk space, CD/DVD-ROM or Internet, USB or Network port; <b>Mac:</b> OS X 10.8 Mountain Lion, OS X 10.9 Mavericks, OS X 10.10 Yosemite; Internet; USB; 1 GB HD; OS compatible hardware (For OS hardware requirements see apple.com)	
<b>Fonts and typefaces</b>	84 scalable TrueType fonts	
<b>Control panel</b>	7.5 cm (3 inch) touchscreen Colour Graphic Display (CGD)	
<b>Power</b>	<b>Power supply type:</b> Internal (Built-in) power supply; <b>Power supply required:</b> 110-volt input voltage: 110 to 127 VAC (+/- 10%), 50/60 Hz (+/- 2 Hz); 220-volt input voltage: 220 to 240 VAC (+/- 10%), 50/60 Hz (+/- 2 Hz) (Not dual voltage, product varies by part number with # Option code identifier); <b>Power consumption:</b> <sup>9</sup> 583 watts (Print/Copy), 9.1 watts (Ready), 2.7 watts (Sleep), 0.7 watts (Auto-On/Auto-Off, via USB connectivity), 0.1 watts (Shutdown or Off)	
<b>Software included</b>	Windows 7: HP Software Installer/Uninstaller, HP PCL 6 Printer Driver, HP Device Experience (DXP), HP Update, HP Device Toolbox, HP Printer Status and Alerts, HP Product Improvement Study, HP Scan App and Driver, Reconfigure your HP Device, Scan to E-mail Wizard, Scan to Network Folder Wizard, Warranty and Legal Guide, User Guide; Windows 8+: HP Software Installer/Uninstaller, HP PCL-6 Printer Driver, HP Device Experience (DXP), HP Scan App and Driver, Warranty and Legal Guide, User Guide, Reconfigure your HP Device; Windows XP, Windows Vista and associated servers: HP Software Installer/Uninstaller, HP PCL 6 Printer Driver, HP Scan App and Driver, Warranty and Legal Guide, User Guide; Mac OS: Welcome Screen (Directs users to HP.com or OS App Source for LaserJet Software)	
<b>Acoustic</b>	<b>Acoustic power emissions:</b> <sup>10</sup> 8 B(A) (printing at 38 ppm); <b>Acoustic power emissions (ready):</b> Inaudible; <b>Acoustic pressure emissions bystander (active, printing):</b> 55 dB(A); <b>Acoustic pressure emissions bystander (ready):</b> Inaudible	
<b>Environmental ranges</b>	<b>Operating temperature range:</b> 15 to 32.5° C (59 to 90.5° F); <b>Recommended operating temperature:</b> 17.5 to 25° C (63.5 to 77° F); <b>Non-operating humidity range:</b> 10 to 90% RH; <b>Operating humidity range:</b> 10 to 80% RH; <b>Recommended operating humidity range:</b> 30 to 70% RH	
<b>Security management</b>	Embedded Web Server: password-protection, secure browsing via SSL/TLS; Network: enable/disable network ports and features, SNMPv1 & SNMPv2 community password change; HP ePrint: HTTPS with certificate validation, HTTP Basic Access Authentication, SASL authentication; LDAP authentication and authorization; Firewall and ACL; SNMPv3, 802.1X, Secure Boot	
<b>Safety approvals and requirements</b>	IEC 60950-1:2005 +A1:2009+A2:2013/EN 60950-1:2006 +A11:2009+A12:2011+A2:2013; IEC 60825-1:2007/EN 60825-1:2007 (Class 1 Laser/LED Product); IEC 62479:2010/EN 62479:2010; GB4943-2011	
<b>Supported network protocols</b>	TCP/IP, IPv4, IPv6; Print: TCP/IP port 9100 Direct Mode, LPD (raw queue support only), Web Services Printing, HP ePrint, Apple AirPrint™, Google Cloud Print 2.0, Mopria, FTP Print, IPP Print, Discovery; SLP Bonjour, Web Services Discovery; IP Config; IPv4 (BootP, DHCP, AutoIP, Manual), IPv6 (Stateless Link-Local and via Router, Stateless via DHCPv6), SSL Security and Certificate management; Management: SNMPv1, SNMPv2, SNMPv3, HTTP/HTTPS, Syslog, FTP FW Download	

<sup>1</sup> Measured using ISO/IEC 24734 Feature Performance Test, excludes first set of test documents. For more information see hp.com/go/printerclaims. Exact speed varies depending on the system configuration, software application, driver, and document complexity.  
<sup>2</sup> Measured using ISO/IEC 17629. For more information see hp.com/go/printerclaims. Exact speed varies depending on the system configuration, software application, driver, and document complexity.  
<sup>3</sup> Scan speed measured from ADF. Actual processing speeds may vary depending on scan resolution, network conditions, computer performance, and application software.  
<sup>4</sup> Measured using ISO/IEC 17629. For more information see hp.com/go/printerclaims. Exact speed varies depending on the input voltage, system configuration, software application, driver, and document complexity.  
<sup>5</sup> Based on standard ITU-T test image #1 at standard resolution and MMR encoding, the HP fax device can transmit at 3 sec/page for V.17. Depending on the input voltage, system configuration, software application, driver, and document complexity.  
<sup>6</sup> Duty cycle is defined as the maximum number of pages per month of imaged output. This value provides a comparison of product robustness in relation to other HP LaserJet or HP Color LaserJet devices, and enables appropriate deployment of printers and MFPs to satisfy the demands of connected individuals or groups.  
<sup>7</sup> HP recommends that the number of pages per month of imaged output be within the stated range for optimum device performance, based on factors including supplies replacement intervals and device life over an extended warranty period.  
<sup>8</sup> Power requirements are based on the country/region where the printer is sold. Do not convert operating voltages. This will damage the printer and void the product warranty.  
<sup>9</sup> Configuration tested: base model, simplex printing, A4 paper at an average of 38 ppm; active scan at 26 ppm.  
<sup>11</sup> Job Storage feature requires a purchase of separate USB flash drive with a minimum of 16 GB capacity.

## To learn more, visit [hp.com](http://hp.com)

© Copyright 2015 HP Development Company, L.P. The information contained herein is subject to change without notice. The only warranties for HP products and services are set forth in the express warranty statements accompanying such products and services. Nothing herein should be construed as constituting an additional warranty. HP shall not be liable for technical or editorial errors or omissions contained herein.

ENERGY STAR and the ENERGY STAR logo are registered U.S. marks. Microsoft and Windows are registered trademarks of Microsoft Corporation. AirPrint and the AirPrint logo are trademarks of Apple Inc., registered in the U.S. and other countries. Linux is a U.S. registered trademark of Linus Torvalds. UNIX is a registered trademark of The Open Group.

